

Wohler GS 300 Gas Sniffer

TECHNICAL DATA

Sensitivity

Methane 0...1.200 ppm
Propane 0...1.200 ppm

Sensor Semiconductor

Alarm function intermittend beep and vibration alarm

Warm-up time approx. 60 sec.

Response time approx. 10 sec.

Environmental conditions

Operating Temperature 23 °F...113 °F

Storage Temperature -4 °F...113 °F

Rel. humidity < 85 %

Auto-off-Function after 20 min

LC-Display 31 x 51 mm

Flashlight 2 LEDs

Connections headphone and power supply unit

Power Supply 4 Mignon-cells AA

Current consumption approx. 100 mA

Dimensions 2.17" x 7.48" x 1.58"

Weight 0.75 lbs